

VC8000 变频器制动组件选型表 (三相 380V~480V)

变频器型号	适配电机 KW	制动单元		125%制动转矩 (10%ED,最大 10 秒)		备注	最小制动电阻值 (Ω)
		型号	数量	推荐制动电阻规格	制动电阻数量		
VC8000-R75G3	0.75	内置标配		140W 800Ω	1		96
VC8000-1R5G3	1.5			300W 380Ω	1		96
VC8000-2R2G3	2.2			440W 260Ω	1		64
VC8000-004G3	4.0			740W 150Ω	1		32
VC8000-5R5G3	5.5			1100W 100Ω	1		32
VC8000-7R5G3	7.5			1500W 75Ω	1		32
VC8000-011G3	11			2200W 50Ω	1		20
VC8000-015G3	15			3000W 38Ω	1		20
VC8000-018G3	18.5			4000W 32Ω	1		24
VC8000-022G3	22			4500W 27Ω	1		24
VC8000-030G3	30	内置选配		6000W 20Ω	1		19.2
VC8000-037G3	37			7000W 16Ω	1		14.8
VC8000-045G3	45		1	9000W 13Ω	1	输入电压≤440Vac	12.8
VC8000-055G3	55		1	11000W 10.5Ω	1	输入电压≤440Vac	9.6
VC8000-075G3	75		1	15000W 7.7Ω	1	输入电压≤440Vac	6.8
VC8000-090G3	90		2	9000W 12.8Ω	2	输入电压≤440Vac	10.5*2
VC8000-110G3	110		2	11000W 10.5Ω	2	输入电压≤440Vac	10.5*2
VC8000-132G3	132		2	13000W 8.8Ω	2	输入电压≤440Vac	7.0*2
VC8000-160G3	160		2	16000W 7.2Ω	2	输入电压≤440Vac	7.0*2
VC8000-185G3	185		2	18000W 6.5Ω	2	输入电压≤440Vac	3.0*2
VC8000-200G3	200		2	19000W 5.8Ω	2	输入电压≤440Vac	3.0*2
VC8000-220G3	220		2	21000W 5.3Ω	2	输入电压≤440Vac	3.0*2
VC8000-250G3	250		2	24000W 4.6Ω	2	输入电压≤440Vac	3.0*2
VC8000-280G3	280		2	27000W 4.1Ω	2	输入电压≤440Vac	3.0*2
VC8000-315G3	315		3	20000W 5.5Ω	3	输入电压≤440Vac	2.5*3
VC8000-355G3	355		3	23000W 4.9Ω	3	输入电压≤440Vac	3.0*3
VC8000-400G3	400		3	26000W 4.3Ω	3	输入电压≤440Vac	3.0*3
VC8000-450G3	450		3	29000W 3.9Ω	3	输入电压≤440Vac	3.0*3